

BACHELOR OF TECHNOLOGY (C.B.C.S.) (2020 COURSE)
B.Tech.Sem - V Electronics & Communication : WINTER-2022
SUBJECT : DIGITAL SIGNAL PROCESSING

Day : Thursday

Time : 02:30 PM-05:30 PM

Date : 8/12/2022

W-24611-2022

Max. Marks : 60

N.B.

- 1) All questions are **COMPULSORY**.
- 2) Figures to the right indicate **FULL** marks.
- 3) Use of non programmable **CALCULATOR** is allowed

Q.1 Prove the following properties of DFT (10)

- i) Linearity
- ii) Complex conjugate property

OR

Q.1 Find IDFT of the sequence (10)

$$X(k) = \{5, 0, 1 - j, 0, 1, 0, 1 + j, 0\}$$

Q.2 An 8 point sequence is given by $x(n) = \{2, 2, 2, 2, 1, 1, 1, 1\}$ Compute 8 point DFT of $x(n)$ by radix - 2 DITFFT (10)

OR

Q.2 Describe the following algorithm (10)

- i) Chirp Z transform
- ii) Goertzel algorithm

Q.3 Design an ideal bandpass filter with a frequency response (10)

$$H_d(e^{j\omega}) = \begin{cases} 1 & \frac{\pi}{4} \leq |\omega| \leq \frac{3\pi}{4} \\ 0 & \text{otherwise} \end{cases}$$

Find the values of $h(n)$ for $N = 11$ & plot the frequency response.

OR

Q.3 Describe design of FIR filters using different windows. (10)

Q.4 Design a chebyshev filter with a maximum passband attenuation of 2.5 dB at $\Omega_p = 20$ rad / sec. of 30 dB at $\Omega_s = 50$ rad / sec. (10)

P.T.O.