

Day: Wednesday
Date: 22/05/2019

S-2019-2733

Time: 02.30 PM TO 05.30 PM
Max. Marks: 60

N.B:

- 1) All questions are **COMPULSORY**.
- 2) Figures to the right indicate **FULL** marks.
- 3) Assume stable data if necessary.
- 4) Use of non programmable **CALCULATOR** is allowed.

- Q.1 a) With neat diagram explain construction and working of SF₆ C.B. (06)
b) What are different types of current limiting reactors? State their advantages and disadvantages. (04)

OR

- Q.1 a) Explain various methods of arc extinction in case of circuit breaker. (06)
b) With neat diagram explain the working of HRC fuse. (04)
- Q.2 a) Determine the time of 5A over-current relay having plug setting of 150% and TMS = 0.4. The CT ratio is 400/5 and the fault current is 6000A. At TMS = 1, the operating time at various PSM are as shown below. (06)

PSM	2	4	5	8	10	20
Time of operation (Sec)	10	5	4	3	2.8	4.0

- b) Draw and explain the trip circuit of circuit breaker. (04)

OR

- Q.2 a) Explain following with related to over-current protective schemes. (06)
i) Time graded system ii) Current graded system
b) Draw and explain the working of directional over current Relay. (04)
- Q.3 a) Explain the phenomenon of over fluxing in transformer and protection against it. (06)
b) A3 phase, 66kV/11kV, Star - Delta connected transformer is protected by differential protection. The CTs on LT side have a ratio of 420/5. Determine the CT ratio on HT side also draw the protection scheme. (04)

OR

- Q.3 a) A 3ph, 10MVA, 11kV alternator is provided with restricted earth fault protection. The percentage of winding protected against phase to earth fault is 80%. The relay trips for 20% out of balance current. Calculate the resistance to be added in neutral to ground connection. (06)
b) Explain the rotor earth fault protection in case of alternator. (04)
- Q.4 a) Explain the fault bus protection of busbar. (06)
b) Explain various effects of arc resistance and power swing on performance of distance relay. (04)

OR

- Q.4 Draw the block diagram of carrier protection scheme of 3 phase transmission line also explain the function of each block. (10)
- Q.5 Explain the lightning phenomenon. Also explain the direct and indirect lightning stroke on the power system. (10)

OR

- Q.5 Explain how lightning arrester provides protection to the power system against over voltages? Also explain Metal oxide (ZnO) type lightning arrester. (10)
- Q.6 Describe the classification of bus bars in substations. Also draw the neat diagram of each. (10)

OR

- Q.6 What are the various equipment used in substation. Explain in detail. (10)